



switch is set as follows:

Dial switch1	Dial switch2	Output sampling rate (24.576M)	Output sampling rate (22.5792M)		
OFF	OFF	48K	44.1K		
ON	OFF	64K	58.8K		
OFF	ON	96K	88.2K		
ON	ON	192K	176.4K		
Dial switch3		Input source			
OFF		USB/Fiber, coaxial (automatic selection)			
ON		I2Sinput			
Dial switch4	Active crystal oscillator				
OFF	24.576M				
ON	22.5792M				

I2SInterface

description
Remarks: see picture for pin sequence.

Pin	Function description
1,3,5,7,9,11	Ground
2	Power Supply 5V
4	SDOUT
6	SDIN
8	LRCLK
10	BCLK
12	MCLK

Instructions for

operation indicator

Red light: at...USBIn the coaxial input state, the signal is always bright and has no signal flicker.

stayI2SInput constant light.

Green light: dial the switch, change the indicator light, change the dial switch status, the green light will go out. (except for the dial switch4)