

Type	Pref.	Ch.	Vmax.	Iq	UGB	Noise Vi @10kHz	CMRR	PSRR	Slew rate V/μS	lib typ.	Vio typ.	Settling 1 0,1%	Settling 2 0,01%	Harm. Dist.	Remarks
AD711KR		1	36 V	2,5 mA	4 MHz	16 nV	80 dB	100 dB	20 V/μS	15 pA	200 μV		1000 nS	-90 dB/10kHz	Precision, High-speed BiFET
AD743JN		1	36 V	8,1 mA	4,5 MHz	2,9 nV	95 dB	96 dB	2,8 V/μS	150 pA	250 μV			-102 dB/10kHz	Ultra low-noise BiFET
AD795JR		1	36 V	1,3 mA	1,6 MHz	9 nV	110 dB	110 dB	1 V/μS	1 pA	100 μV	10000 nS	11000 nS	-80 dB/10kHz	Low noise, Low power, precision FET
AD8065A		1	26,4 V	6,6 mA	145 MHz	7,0 nV	100 dB	93 dB	180 V/μS	3 pA	400 μV	55 nS	250 nS	-100dB/1MHz	High Performance FastFet
AD817		1	36 V	7,0 mA	50 MHz	15 nV	120 dB	86 dB	350 V/μS	3,3 uA	500 μV	45 nS	70 nS	-78dB/10kHz	High-speed, Low Power
AD826		2	36 V	13,6 mA	50 MHz	15 nV	120 dB	86 dB	350 V/μS	3,3 uA	500 μV	45 nS	70 nS	-92 dB/10kHz	High-speed, Low Power
AD827J		2	36 V	10,5 mA	50 MHz	15 nV	95 dB	86 dB	300 V/μS	3,3 uA	4 mV max.	120 nS		-90 dB/10kHz	High-speed, Low Power
AD8510B	R2	1	36 V	4,4 mA	8 MHz	7,6 nV	108 dB	100 dB	20 V/μS	25 pA	80 μV	500 nS	900 nS	-102 dB/10kHz	Precision, Very Low Noise, Low Input Bias, Wide Band, JFET
AD8610B	R1	1	27,3 V	6,0 mA	25 MHz	6 nV	110 dB	110 dB	60 V/μS	3 pA	45 μV		600 nS	-104 dB/10kHz	Precision, Very Low Noise, Low Input Bias, Wide Band, JFET
AD8627AR		1	27 V	0,71 mA	5 MHz	16 nV	105 dB	104 dB	5 V/μS	0,25 pA	350 μV	1250 nS		-84 dB/10kHz	Precision, Low power JFET
AD8671AR		1	36 V	3,0 mA	10 MHz	2,8 nV	120 dB	130 dB	4 V/μS	3 nA	20 μV	2200 nS	6300 nS	-104 dB/10kHz	Precision, Very Low Noise, Low Input Bias
AD8675AR		1	36 V	2,5 mA	10 MHz	2,5 nV	120 dB	110 dB	1 V/μS	2,5 nA	20 μV				Precision, Low Noise, Rail-to-rail Output
EL2244		2	36 V	5,2 mA	60 MHz	15 nV	90 dB	80 dB	250 V/μS	2,8 uA	500 μV	80 nS		-55 dB/10kHz	Low power, unity gain stable
LF356		1	36 V	5,0 mA	5 MHz	12 nV	100 dB	100 dB		30 pA	3 mV		1500 nS		
LM6172IN		2	36 V	4,6 mA	100 MHz	12 nV	110 dB	95 dB	3000 V/μS	1,2 uA	400 μV	65 nS		-110 dB/10kHz	High-speed, Low Distortion
LT1056A		1	40 V	5,0 mA	6,5 MHz	14 nV	100 dB	106 dB	16 V/μS	10 pA	50 μV	900 nS	1800 nS		Precision High-speed J-FET
LT1122A		1	40 V	7,5 mA	14 MHz	14 nV	99 dB	103 dB	80 V/μS	10 pA	120 μV		340 nS	-103 dB/10kHz	Fast settling J-FET
LT1360		1	36 V	4,0 mA	50 MHz	9 nV	92 dB	105 dB	800 V/μS	300 nA	300 μV	60 nS	90 ns	-99 dB/10kHz	High-speed, High Performance
LT1361	*	2	36 V	4,0 mA	50 MHz	9 nV	92 dB	105 dB	800 V/μS	300 nA	300 μV	60 nS	90 nS	-99 dB/10kHz	High-speed, High Performance
LT1363		1	36 V	6,3 mA	70 MHz	9 nV	90 dB	100 dB	1000 V/μS	600 pA	500 μV	50 nS	80 ns	-100 dB/10kHz	High-speed, High Performance
NE5534A		1	44 V	4,0 mA	10 MHz	3,5 nV	100 dB	100 dB	13 V/μS	500 nA	500 μV			-90 dB/10kHz	Low noise, High Performance
OP249		2	36 V	5,6 mA	4,7 MHz	16 nV	90 dB	98 dB	22 V/μS	30 pA	200 μV	700 nS	800 nS	-91 dB/10kHz	High-speed, Precision JFET
OP275		2	22 V	8,0 mA	9 MHz	6 nV	106 dB	111 dB	22 V/μS	100 nA	1 mV max.			-84 dB/1kHz	Bipolar/JFET Audio
OPA124UA		1	30V	2,5 mA	1,5 MHz	6 nV	110 dB	110 dB	1,6 V/μS	0,5 pA	150 μV	6000 nS	10000 nS	-110 dB	Low noise Precision DI-FET
OPA132U	*	1	36 V	4,0 mA	8 MHz	8 nV	100 dB	105 dB	20 V/μS	5 pA	250 μV	700 nS	1000 nS	-118 dB/10kHz	High-speed FET-input
OPA132UA		1	36 V	4,0 mA	8 MHz	8 nV	94 dB	105 dB	20 V/μS	5 pA	500 μV	700 nS	1000 nS	-118 dB/10kHz	High-speed FET-input
OPA134UA		1	36 V	4,0 mA	8 MHz	8 nV	100 dB	105 dB	20 V/μS	5 pA	500 μV	700 nS	1000 nS	-118 dB/10kHz	SoundPlus High Performance Audio
OPA2134PA		2	36 V	4,0 mA	8 MHz	8 nV	100 dB	105 dB	20 V/μS	5 pA	500 μV	700 nS	1000 nS	-118 dB/10kHz	SoundPlus High Performance Audio
OPA227P		1	36 V	3,7 mA	8 MHz	3 nV	138 dB	130 dB	10 V/μS	2,5 nA	5 μV	5000 nS	5600 nS	-107 dB/10kHz	High Precision, Low Noise
OPA602BP	*	1	36 V	3,0 mA	6,5 MHz	12 nV	100 dB	100 dB	35 V/μS	1 pA	500 μV	600 nS	1000 nS	-88 dB/10kHz	Precision High-speed Difet
OPA604A		1	48 V	5,3 mA	20 MHz	10 nV	100 dB	100 dB	25 V/μS	50 pA	1 mV	1000 nS	1500 nS	-106 dB/10kHz	FET-Input, Low Distortion
OPA2604AP		2	48 V	5,3 mA	20 MHz	10 nV	100 dB	80 dB	25 V/μS	100 pA	1 mV	1000 nS	1500 nS	-106 dB/10kHz	FET-Input, Low Distortion
OPA606KP		1	36V	6,6 mA	12 Mhz	12 nV	90 dB	90 dB	30 V/μS	8 pA	300 μV	1000 nS	2100 nS	-89 dB/10kHz	Wideband DiFET
OPA627B	S1	1	36 V	3,5 mA	16 MHz	4,5 nV	116 dB	120 dB	55 V/μS	1 pA	100 μV	450 nS	550 nS	-113 dB/10kHz	Precision High-speed Difet
THS4001		1	32 V	7,8 mA	270 MHz	12,5 nV	100 dB	85 dB	400 V/μS	2,6 uA	2 mV	40 nS		-72 dB/1MHz	High-speed Voltage-Feedback
THS4011	S2	1	32 V	7,8 mA	290 MHz	7,5 nV	110 dB	83 dB	310 V/μS	2 uA	1 mV	37 nS	90 nS	-80 dB/1MHz	Low Distortion, High-speed
THS4081		1	30 V	3,4 mA	175 MHz	10 nV	90 dB	90 dB	230 V/μS	1,2 uA	1 mV	43 nS	233 nS	-79 dB/1MHz	Low-power High-speed
TL071C		1	36 V	1,4 mA	4 MHz	15 nV	86 dB	86 dB	16 V/μS	20 pA	3 mV			-87 dB/10kHz	Low noise J-FET
TLE2071A		1	38 V	1,7 mA	10 MHz	11,5 nV	98 dB	99 dB	40 V/μS	20 pA	470 μV	400 nS	1500 nS	-78 dB/10kHz	Excalibur Low-noise High-speed JFET