

Schematic Ref. No.	Part No.	Description	Schematic Ref. No.	Part No.	Description
	BA05716A	Main P.C.B. Ass'y	ZD401	OB12197A	ZD 27V
	— MC Amp. —		ZD402	OB16191A	RD27JS-T1B1
Q101,201	OB06376A	FET 2SK170 (GR)	D401	OB06282A	ZD 2.7V RD2.7E
VR101,201	OB32044A	Semi-fixed VR 5K	D402,403	OB12097A	Diode Bridge DBA10
R103,203	OB09203A	RM 10K 1/4W F	R401		SiD 1SS55
R104,204	OB09446A	RM 33.2K 1/4W F	R402,404	OB09305A	RM 100K 1/4W F
R105,205	OB09540A	RM 3.24K 1/4W F	R403	OB09203A	RM 10K 1/4W F
R106,206	OB09305A	RM 100K 1/4W F	R405	OB09491A	RM 1K 1/4W F
R107,108	OB09547A	RM 2.21K 1/4W F	R406	OB24066A	RF 3.3 1/2W J
207,208			R407	OB22652A	RM 820 1/4W F
R136,236	OB09491A	RM 1K 1/4W F	R408	OB09427A	RM 5.62K 1/4W F
C103,203	OB41547A	CP 3600P 100V F	C401,402	OB09900A	RM 4.99K 1/4W F
C104,107	OB40333A	CE 470μ 25V	C404	OB40332A	CE 1800μ 50V
108,204			C405	OB40334A	CE 100μ 35V
207,208			C406	OB40335A	CE 470μ 50V
C105,205	OB41545A	C 300P 100V J		OB40116A	CE 10μ 50V
C106,206	OB41543A	CM 1μ 125V		OB81375A	Screw Terminal P-100 (2)
	— Eq. Amp. —			OB81376A	Screw Terminal P-104 (2)
Q102,202	OB06365A	FET 2SK240 (GR)		OB90077A	Bus Line Plate (3)
Q103,108	OB10102A	TR 2SA1320		— Miscellaneous —	
203,208				OB60223A	Main P.C.B.
Q104,106	OB10103A	TR 2SC3333		OB82424A	12P Connector SCN-CN
107,204					12P-12P (1)
206,207				OB82425A	8P Connector SCN-CN
Q105,205	OB10105A	FET 3N172			8P-8P (2)
D101-104	OB06181A	SiD 1SS53 (8)		OB82426A	8P Connector SCN-CN
201-204					8P-4Px2 (1)
R109,113	OB09491A	RM 1K 1/4W F		OB82427A	4P Connector SCN-CN
125,209					4P-2Px2 (1)
213,225				OB82428A	4P Connector SCN-CN
R110,210	OB22638A	RM 47.5K 1/4W F			4P-2Px2 (1)
R111,120	OB22639A	RM 681 1/4W F		OB82429A	4P Connector SCN-CN
211,220					4P-2Px2 (1)
R112,212	OB09760A	RM 332 1/4W F		OB82430A	2P Connector SCN-CN
R114,115	OB09340A	RM 15K 1/4W F			2P-2P (1)
214,215				OB82431A	2P Connector SCN-CN
R116,119	OB22576A	RM 475 1/4W F			2P-2P (1)
216,219				OB82486A	4P Connector SCN-CN
R117,217	OB22641A	RM 887K 1/4W F			(1)
R118,218	OB09562A	RM 75K 1/4W F			
R121,221	OB22642A	RM 221 1/4W F			
R122,123	OB09177A	RF 47 1/4W J			
222,223					
R124,224	OB09305A	RM 100K 1/4W F			
C109,209	OB41561A	C 100P 100V J			
C110,210	OB41546A	C 20μ 200V K			
C111,211	OB41547A	CP 3600P 100V F			
C112,212	OB41548A	CP 1000P 100V F			
C113,213	OB41542A	C 40P 100V J			
C114,214	OB41544A	C 200P 100V J			
C115,215	OB41536A	CM 10μ 200V K			
TF101,201	OB08715A	Thermal Fuse 129			
	— Line Amp. —				
Q109,209	OB06365A	FET 2SK240 (GR)			
Q110,112	OB10103A	TR 2SC3333			
210,212					
Q111,211	OB10102A	TR 2SA1320			
D105,106	OB06181A	SiD 1SS53			
205,206					
R126,135	OB09491A	RM 1K 1/4W F			
226,235					
R127,134	OB09305A	RM 100K 1/4W F			
227,234					
R128,228	OB22639A	RM 681 1/4W F			
R129,229	OB09760A	RM 332 1/4W F			
R130,230	OB09547A	RM 2.21K 1/4W F			
R131,231	OB22640A	RM 22.1K 1/4W F			
R132,232	OB09340A	RM 15K 1/4W F			
R133,233	OB22642A	RM 221 1/4W F			
C117,217	OB41561A	C 100P 100V J			
C118,218	OB41542A	C 40P 100V J			
C119,219	OB41536A	CM 10μ 200V K			
RL301	OB90086A	MR Relay			
	— DC Supply —				
IC401	OB11165A	IC NJM7824			
IC402	OB11166A	IC NJM7924			
Q401,402	OB10103A	TR 2SC3333			
406					
Q403,404	OB10102A	TR 2SA1320			
Q405	OB06255A	TR 2SD880			