

*"SNAPTROL" ① Use QCBI instead of TAB MOUNT PLATE IN TMO.

TRANSFORMER (POWER)

ITEM No.	RATING			REPLACEMENT DATA					NOTES
				Zenith PART No.	MERIT PART No.	STANCOR PART No.	THORDARSON PART No.	TRIAD PART No.	
	PRI.	SEC. 1	SEC. 2						
T2	117VAC ⓐ .6A	690VCT ⓑ .070A	5VAC ⓒ 2A	95-1953	P3152①	PC8409①	24R40U①	R-111A	① Drill New Mounting hole(s).
	SEC. 3	SEC. 4	SEC. 5						
	6.3VCT ⓓ 1.7A								

TRANSFORMER (AUDIO OUTPUT)

ITEM No.	IMPEDANCE		REPLACEMENT DATA					NOTES
			Zenith PART No.	MERIT PART No.	STANCOR PART No.	THORDARSON PART No.	TRIAD PART No.	
	PRI.	SEC.						
T3	9,600Ω Tap③ 9%	6-8Ω	95-1957					
T4	9,600Ω Tap③ 9%	6-8Ω	95-1957					

SPEAKER

ITEM No.	TYPE			REPLACEMENT DATA		NOTES
				Zenith PART No.	QUAM PART No.	
SP1	10"	PM	6-8Ω	49-950	10A31PA	
SP2	4"	PM	14-16Ω	49-967	4A07Z14	
SP3	3 1/2"	PM	45-50Ω	49-978	3A15T250	
SP4	10"	PM	6-8Ω	49-950	10A31PA	
SP5	4"	PM	14-16Ω	49-967	4A07Z14	
SP6	3 1/2"	PM	45-50Ω	49-978	3A15T250	

ELI CEC