

FENDER SIDEKICK SWITCHER, BASS, KEYBOARD

PARTS LIST

DESCRIPTION	MODEL	PARTS NUMBER	SWITCHER	BASS	KEYBOARD
IC-POWER	LM1875T	025642	1	1	1
IC-OPAMP	MS218P	025118	6	3	3
IC-VCA	CA3080	025644	-	1	-
TRANSISTOR	2SA1015GR	025121	2	-	1
	2SC1815GR	022864	2	1	1
FET	2SK30GR	022865	4	1	1
DIODE	1S1588	022868	12	7	10
	2SE10C	025133	2	2	2
DIODE ZENER	GZA12	025645	-	2	2
	RD15F	022832	2	-	-
DIODE BRIDGE	DBA30C	025132	1	1	1
LED PILOT	SEL-1110R	022908	1	2	2
LED CHANNEL	TLR-206	025472	2	-	-
RESISTOR	1/4W 56 OHM	025144	1	-	-
	100 OHM	016934	3	1	-
	270 OHM	025147	5	-	-
	470 OHM	022874	1	-	2
	820 OHM	024102	2	-	-
	1K OHM	022975	6	4	2
	1.5K OHM	022976	2	1	-
	2.2K OHM	022977	6	1	-
	2.7K OHM	025151	3	3	8
	3.3K OHM	022979	1	-	1
	4.7K OHM	022877	1	1	1
	6.8K OHM	025152	2	-	-
	10K OHM	022878	12	6	7
	12K OHM	022880	1	-	-
	15K OHM	024103	1	1	3
	22K OHM	022981	1	5	4
	27K OHM	025157	1	-	1
	33K OHM	024104	5	3	2
	39K OHM	025646	-	-	1
	47K OHM	022982	3	1	1
	56K OHM	022984	-	2	-
	68K OHM	022985	-	2	2
	82K OHM	025647	-	-	1
	100K OHM	022987	14	4	1
	120K OHM	025648	-	1	-
	130K OHM	022833	-	-	2
	220K OHM	025649	1	2	3
	390K OHM	022883	-	1	-
	470K OHM	022884	2	-	-
	1M OHM	022990	4	-	4
	2.2M OHM	022991	-	1	1
	5.6M OHM	025651	-	-	1
RESISTOR	1/2W 750 OHM	025652	-	-	2
RESISTOR	1 W 0.5 OHM	025653	1	1	1
	1 W 180 OHM	025654	2	-	-
	1 W 220 OHM	025168	1	1	1
	1 W 470 OHM	026848	-	2	-
CAPACITOR ELE	1 MFD-50V	022899	10	5	4
	4.7 MFD-25V	070060	2	-	-
	10 MFD-25V	021105	6	4	7
	22 MFD-16V	025181	1	-	-
	47 MFD-25V	025182	3	-	-
	100 MFD-25V	025183	2	1	2
	330 MFD-16V	022904	1	1	-
	3300 MFD-35V	023020	2	2	2
CAPACITOR MYL	0.001 MFD	024118	1	-	1
	0.0047 MFD	023012	-	1	1
	0.0068 MFD	022892	-	1	2
	0.01 MFD	023013	1	-	2
	0.015 MFD	025193	-	-	1
	0.022 MFD	022893	1	3	1
	0.047 MFD	022896	2	1	-
	0.068 MFD	025191	1	-	-
	0.1 MFD	023014	11	5	6
	0.15 MFD	024113	1	-	-
CAPACITOR DISK	10 PF	023007	2	-	1


DESCRIPTION	MODEL	PARTS NUMBER	SWITCHER	BASS	KEYBOARD
	33 PF	023008	-	1	-
	47 PF	022890	1	-	-
	100 PF	023009	3	2	3
	220 PF	025175	-	2	5
	270 PF	025176	1	-	-
	470 PF	023049	1	1	2
CAPACITOR MP.O	0.33 MFD-50V	026850	1	1	2
	0.15 MFD-100V	026851	1	1	1
CONTROL 18S	10 KA	026852	-	1	-
	10 KL	025201	2	2	3
	10 KRA	025207	1	-	-
	50 KL	025199	3	-	3
	50 KRA	025200	3	-	-
	250 KA	025196	1	2	-
	250 KL	025198	1	-	-
JACK	TJ-125-020-01	022922	1	3	3
	TJ-125-060-01	022923	1	1	1
	TJ-125-080-01	025210	2	-	-
P.C.BOARD	PCSK530	026853	1	-	-
	PCSKB30	026855	-	1	-
	PCSKK30	026857	-	-	1
CHASSIS	C-SKSW	026858	1	-	-
	C-SKB30	026859	-	1	-
	C-SKK30	026860	-	-	1
PANEL-FRONT	FP-SKSW	026861	1	-	-
	FP-SKB30	026863	-	1	-
	FP-SKK30	026865	-	-	1
PANEL-REAR	BP-SKSW	026866	1	-	-
	BP-SKB30	026867	-	1	-
	BP-SKK30	026868	-	-	1
NAME-PLATE	NP-SKSW	026869	1	-	-
FENDER LOGO	FL-2	011298	1	1	1
KNOB (CONTROL)	FK-2	025300	11	5	6
KNOB (POWER)	GP-10A (BLACK)	026870	-	1	1
POWER TRANS	F31UC	026871	1	-	-
	T31UC	026873	-	1	1
POWER CORD	SJT-2.4M	022926	1	1	1
POWER SWITCH	CTA-01	025279	1	-	-
	ES899682V	026874	-	1	1
LAG TERMINAL	2L4P	025299	1	-	-
FUSE HOLDER	FH-032	022924	1	-	-
FUSE CLIP	F-208	025223	-	2	2
FUSE	61W 1.5A	022928	1	1	1
HEATSINK	HS-SKSW	026875	1	-	-
	HS-SKBK	026876	-	1	1
CABINET W/T.G	CAB-SK35R	025306	1	-	-
	CAB-SKB30	026877	-	1	-
	CAB-SKK30	026878	-	-	1
HANDLE	HSK-FE	025318	1	-	-
	HSK-10	019170	-	1	1
HANDLE CAP	HCSK-20	019276	2	2	2
CORNER	CFE-1	024695	6	-	-
	CFE-2	026879	-	6	6
GLIDE ASSY	PFSK-50	019308	4	-	-
	No-7105	026881	-	4	4
SPEAKER	PFG-1220	026882	1	-	-
	PFB-1020	026883	-	1	-
	PFK-1012	026884	-	-	1
REVERB PAN	SR-01542CE	025269	1	-	-
FOOT-SW CHASS	FT-2	026885	1	-	-
FOOT-SW BOTTM	FT-RUBBER	026886	1	-	-
FOOT-SW LABEL	R/C	026887	1	-	-
FOOT-SW CORD	MIC-SW	026889	1	-	-
SWITCH (F/SW)	DS-139	026890	2	-	-
	FOR POWER-SW	026892	1	-	-
P.C.B SUPORT	PCB-4L	023088	3	-	-
	KGLS-18S	026893	-	3	2
CORD BUSH	SRGN4	025301	1	-	-
	SRSP4	026894	3	-	-

DESCRIPTION	MODEL	PARTS NUMBER	SWITCHER	BASS	KEYBOARD
	KF21	021691	1	-	-
CORD GLIP	KD-5N	022955	2	1	1
CONVEX	CV-70	025415	10	7	7
LABEL	GLF-1	025418	1	1	1
	CAUTION	025417	1	1	1
	SERIAL	025449	1	1	1
	PASS	026895	1	1	1
WIRE ASSY	W-SKSW	026897	1	-	-
	W-SKBA	026899	-	1	-
	W-SKKB	026900	-	-	1
SCREW PAN	3x6 W/SW+FW	025326	3	3	3
	3x8 W/SW	025328	1	0	0
	3x10 W/SW	026933	0	1	1
	3x8 W/SW+FW	025327	4	2	2
	4x6	025333	2	1	1
	4x8 W/SW+FW	026901	-	2	2
SCREW PAN TP	3x8 W/SW+FW	026902	4	-	-
SCREW OVAL TP	3.1x25 Ni	025345	8	-	-
	3.8x16 Ni	025348	8	-	-
SCREW OVAL	4x30 BLACK	022957	4	4	4
	4x35 Ni	026903	-	4	4
	5x25 Ni	024126	4	-	-
SCREW TRUS	3x6 BLACK	026905	-	2	2
SCREW TRUS TP	2.6x10 BLACK	025342	4	2	2
	3x10 Ni	026911	-	12	12
	3x12 BLACK	026907	2	2	2
	3x12 Ni	026908	4	-	-
	3x25 BLACK	026909	-	10	10
	4x20 BLACK	025340	-	4	4
	4x30 BLACK	025339	4	-	-
SCREW FLAT WOOD	4x25	025344	4	-	-
WASHER	ROSSETTE 3mm Ni	025352	8	-	-
	ROSSETTE 4mm B	022958	4	4	4
	IN-LOCK 4mm	025350	2	2	2
NUT	FLANGE 4mm	022964	4	8	8
CARTON	CA-SKSW	026913	1	-	-
	CA-SKBA	026915	-	1	-
	CA-SKKB	026916	-	-	1
CORNER CUSHION	20mm	025444	8	8	-
VINYL PACKAGE	PE04	025447	1	1	1
	No.2	025929	-	-	1
	No.3	025632	1	-	-
	No.4	025636	-	1	-
	No.9	026917	1	-	-
WARRANTY CARD		025358	1	1	1
MANUAL	MNU-SKSW	026918	1	-	-
	MNU-SKBA	026919	-	1	-
	MNU-SKKB	026921	-	-	1
EXPORT MODEL	ONLY				
POWER CORD	EUROPE	022927	1	1	1
POWER TRANS	F31S	026923	1	-	-
	T31S	026924	-	1	1
CHASSIS	C-SKSW-S		1	-	-
PANEL-FRONT	FP-SKSW-S		1	-	-
	FP-FB30	026925	-	1	-
	FP-FKB30	026926	-	-	1
REAR-PANEL	BP-SK-SW-S		1	-	-
	BP-SKB30S		-	1	-
	BP-SKK30S		-	-	1
NAME-PLATE	NP-FSW	026927	1	-	-
FUSE HOLDER	FH-033(EUR)	026928	1	-	-
	FH-802(SEMCO)	026929	1	-	-
FUSE CLIP	F-206	026931	-	2	2
FUSE	ES-3 0.8A	026932	1	1	1
INSULATION /P	FOR F-HOLDER	026891	1	-	-
POWER SWITCH	1852.0122		1	-	-
CORD CLIP	EA-1702B		2	-	-
CORD BUSH	KR-61	024122	1	-	-

SK
Keyboard
switches
BASS
30
WATT

SIDEKICK-BASS

LINE OUT



- 1 - WV AC VOLTAGES DENOTE TYPICAL 1 KHZ SIGNAL WITH AMP SET IN EACH CHANNEL.
ALL CONTROLS SET TO MAXIMUM
- 6 - ALL DIODES ARE 1S158B UNLESS NOTED
- 5 - IC 5 IS LM1875T
- 4 - IC 3 IS CD3000
- 3 - IC 1 TO 4 ARE M5218P
- 2 - ALL RESISTOR VALUES ARE IN OHM, 1/4 W 5 %
- 1 - ALL CAPACITOR VALUES ARE IN MICROFARAD

作成	設計	調達	承認	品名		記事		図面変更
K. Yamazaki				図番		尺度		N
				材質				N
							N	
							N	
図面作成		年 月 日		ELK ELECTRIC INC ☎ 0286 61 - 4000 29 - 5 HIRAIDE - KOGYODANCHI UTSUNOMIYA JAPAN				

FEB/14/1987



- 6 - **HV** AC VOLTAGES DENOTE
TYPICAL 1 KHZ SIGNAL WITH
AMP SET IN EACH CHANNEL.
ALL CONTROLS SET TO
MAXIMUM, REVERB OFF
- 5 - ALL DIODES ARE 1S15BB UNLESS
NOTED
- 4 - IC 7 IS LM1875T
- 3 - IC 1 TO 6 ARE MS21BP
- 2 - ALL RESISTOR VALUES ARE
IN OHM, 1/4 W 5 %
- 1 - ALL CAPACITOR VALUES ARE
IN MICROFARAD

[illegible]