



## SYSTEM COMPONENTS:

### LOW FREQUENCY DRIVER:

Cone Kit:	123A-1
Nom. Impedance:	C8R2212
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	6
D.C. Resistance Ohms:	20-1200
	4.5 minimum
	5.5 maximum
Gap Gauge:	.044"
Notes:	Aquaplas
If Not Serviceable,	2213H
Replace With:	(Reverse Polarity)
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No.
	Slightly different. Replace both units
	in a stereo pair.

#### Additional Parts Currently Available\*:

Dome:	31385
Trim Gasket:	32756

### MID RANGE DRIVER:

Cone Kit:	LE5-2
Nom. Impedance:	C8RLE52
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	4
D.C. Resistance Ohms:	75-3000
	5.5 minimum
	6.5 maximum

Gap Gauge:	.040"
Notes:	Dome Inverted

If Not Serviceable,

Replace With: LE5-10

Visual Change: Yes

Baffle Modification: No

Exact Acoustic Replacement: No.

Slightly different. Replace both units  
in a stereo pair.

### MID RANGE DRIVER (Cont'd)

#### Additional Parts Currently Available\*:

Dome:	54721
Trim Gasket:	29931

### HIGH FREQUENCY DRIVER:

Diaphragm Kit:	LE20-1
Nom. Impedance:	D8RLE20
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	6
D.C. Resistance Ohms:	1000-6000
	3.7 minimum
	4.2 maximum

Gap Gauge:

Notes:

If Not Serviceable,

Replace With:

Visual Change: 035TiA

Baffle Modification: Yes

Exact Acoustic Replacement: No. Use as a last  
resort. Replace both units in a stereo pair.

#### Additional Parts Currently Available\*:

Trim Ring:	21600
------------	-------

## SYSTEM SPECIFICATIONS:

Nominal Impedance:	8 Ohm
Power Capacity:	50 Watts
	Continuous Program
Crossover Frequencies:	2500 Hz, 7500 Hz
Sensitivity:	78dB (1 Watt @ 15 Feet)
Enclosure Dim:	14-1/2" x 23-1/2" x 13-3/4" D
	37cm x 60cm x 35cm
Shipping Weight:	54 lbs. - 24 kg.
Additional Parts Currently Available*:	
Grill:	G100-Cloth
Binding Posts: Red:	10243
Black:	10244

\*Other parts may also be available. Check with JBL for details.