



TYPES OF CATHODES AND THEIR USE

In electron tubes, a cathode is an electrode which is the primary source of electron or ion emission. There are two broad classes of cathodes, i.e., hot and cold. "Hot cathodes" are defined as cathodes which are heated or otherwise operate at elevated temperature (frequently incandescent) in order to function as emitters. In contrast, "cold cathodes" are defined as cathodes which do not rely on heat or on elevated temperature in order to function as emitters.

HOT CATHODES

Hot cathodes commonly in use in electron tubes are classified as directly heated, indirectly heated, and ionic-heated.

A directly heated cathode, or filament-cathode, is a wire or ribbon which is heated by the passage of current through it. It is further classified by identifying the filament material or the electron-emitting material. Such materials in regular use are pure tungsten, thoriated tungsten, and metals coated with alkaline-earth oxides. Each of these materials has distinctive advantages which are utilized in the design of tubes for particular applications.

PURE-TUNGSTEN FILAMENTS are used in certain tubes, especially those for high-voltage transmitting service. Since these filaments must operate at a high temperature of about 2500°C (a dazzling white) to emit sufficient electrons, a relatively large amount of filament power is required. The operating life of these filaments is determined by the rate of tungsten evaporation. Their failure, therefore, occurs through decreased emission or burn-out.

Pure-tungsten filaments give best life performance when they are operated so as to conserve their emitting capability. They are designed with voltage and current ratings in accord with the service expected of the particular tube type. However, in applications where the normal emission at rated voltage is not



TYPES OF CATHODES

(continued from preceding page)

required, the filament can be operated at a somewhat reduced voltage. The extent of the reduction depends on the peak emission requirements of the application as well as on the percentage regulation of the filament voltage. When these are known, the correct operating filament voltage for any tungsten-filament type can be calculated from its filament-emission characteristic. The permissible regulation in transmitters may be checked by reducing the filament voltage (with the transmitter under normal operation) to a value such that reduction in output can just be detected. The filament voltage must then be increased by an amount equivalent to the maximum percentage regulation of the filament-supply voltage and then increased further by approximately 2 per cent to allow for minor variations in emission of individual tubes. It follows that the better the regulation, the less the filament operating voltage and, therefore, the longer the filament life.

It should be noted that a reduction of 5 per cent in the filament voltage applied to tubes with pure-tungsten filaments will approximately double their life. A reduction of 15 per cent will increase the filament life almost tenfold.

During long or frequent standby periods, pure-tungsten-filament tubes may be operated at decreased filament voltage to conserve life. When the average standby time is an appreciable portion of the average duty cycle and is less than 2 hours, it is recommended that the filament voltage of all but the largest types be reduced to 80 per cent of normal; and that for longer periods, the filament power be turned off. For the largest types, such as the 898, it is recommended that the filament voltage be reduced to 80 per cent of normal during standby operation up to 12 hours; and that for longer periods, the filament power be turned off.

For turning on filament power, a filament starter should be used so as to increase the voltage gradually and to limit the high initial rush of current through



TYPES OF CATHODES

(continued from preceding page)

the filament. It is important that the filament current never exceed, even momentarily, a value of more than 150 per cent of normal, unless the tube data specify otherwise. Similarly, as an added precaution, the filament power should be turned off gradually to prevent cooling strains in the filament.

THORIATED-TUNGSTEN FILAMENTS are now used mainly in certain transmitting and special tubes. Thoriated-tungsten filaments are made from tungsten impregnated with thoria. Due to the presence of thorium, these filaments liberate electrons at a more moderate temperature of about 1700°C (a bright yellow), and are, therefore, much more economical of filament power than are pure-tungsten filaments. The operating life of thoriated-tungsten filaments is ordinarily ended by a decrease in electron emission. Decreased emission, however, may be caused by the accidental application of too high filament, screen, or plate voltage. If the over-voltage has not been continued for a long time, the activity of the filament can often be restored by operating the filament at its normal voltage for 10 minutes or longer without plate, screen, or grid voltage. The reactivation process may be accelerated by raising the filament voltage to not higher than 120 per cent of normal value for a few minutes. This reactivation schedule is often effective in restoring the emission of thoriated-tungsten filaments in tubes which have failed after normal service. Sometimes a few hundred hours of additional life may be obtained after reactivation.

The operating voltage of a thoriated-tungsten filament should, in general, be held to within ± 5 per cent of its rated value. However, in transmitting applications where the tube is lightly loaded, the filament may be operated on the low side—as much as 5 per cent below normal voltage. As conditions require, the voltage should be increased gradually to maintain output. Toward the end of life, additional service may be obtained by operating the fila-



TYPES OF CATHODES

(continued from preceding page)

ment above its rated voltage. It should be noted that a tube having a thoriated-tungsten filament should never be operated under emission-limited conditions since this type of operation may overheat the tube and cause permanent loss of emission.

During standby periods in transmitting service, thoriated-tungsten filaments may be operated according to the following recommendations to conserve life. For short standbys of less than 15 minutes duration, the filament voltage of all but the largest types should be reduced to 80 per cent of normal; for longer periods, the filament power should be turned off. For the largest types, such as the 827-R and 861, it is recommended that the filament voltage be reduced to 80 per cent of normal during standby operation up to 2 hours; and that for longer periods, the filament power be turned off.

COATED FILAMENTS are used in receiving tubes, certain transmitting tubes, most mercury-vapor rectifiers, and some special tubes. Coated filaments employ a relatively thick coating of alkaline-earth compounds on a metallic base as a source of electronic emission. The metallic base carries the heating current. These filaments operate at a low temperature of about 800°C (a dull red) and require relatively little power to produce a copious supply of electrons.

For proper performance of these types, rated filament voltage should, in general, be applied at the filament terminals. However, when coated-filament, high-vacuum tubes are used in transmitting service with light loading, the filament voltage may be reduced as much as 5 per cent below normal to conserve life. Then, as conditions require, the voltage should be increased gradually to maintain output. Toward the end of life, the gradual increase may be carried above rated filament voltage to obtain additional service. In the case of gas or vapor tubes, it is important that these types be operated, in general, at rated filament voltage. However, if the line regu-



TYPES OF CATHODES

(continued from preceding page)

lation regularly and consistently does not exceed 1 to 2 per cent, it is practical to reduce the filament voltage slightly (not over 5 per cent) with benefit to tube life.

During standby periods of less than 15 minutes, the filament voltage of quick-heating, high-vacuum types, such as the 1616 and 1624, should be reduced to 80 per cent of normal; for longer periods, the filament power should be turned off. In contrast, the voltage of coated filaments in gas or vapor tubes should not be reduced during standbys except under conditions explained in the preceding paragraph. In general, the filament voltage of small and medium types, such as the 866-A/866 and 872-A/872, should be maintained at normal rated value during standbys up to 2 hours; for longer periods, the filament power should be turned off. For large types, such as the 857-B, the filament voltage should be maintained at normal rated value during standbys up to 12 hours; for longer periods, the filament power should be turned off.

After having given normal service or after having been operated at excessive voltage, coated filaments lose their emission. When such is the case, their usefulness may be considered as terminated.

An indirectly heated cathode, or heater-cathode, consists of a heater wire enclosed in a thin metal sleeve coated on the outside with electron-emitting material similar to that used for coated filaments. The sleeve is heated by radiation and conduction from the heater through which current is passed. Useful emission does not take place from the heater wire. An important feature of this kind of cathode construction is that the functions of heating and emission can be independent of each other.

HEATER-CATHODES, or unipotential cathodes as they are frequently called, are used in high-vacuum tubes operating at low plate voltage, such as receiv-



TYPES OF CATHODES

(continued from preceding page)

ing tubes, low-power transmitting tubes, and small special tubes. They also find application in mercury-vapor tubes and in cathode-ray tubes. Heater-cathodes, like coated filaments, provide a copious supply of electron emission at low cathode temperature (a dull red).

For proper performance of heater-cathode tubes, rated heater voltage should, in general, be applied at the heater terminals. However, when heater-cathode high-vacuum tubes are used in transmitting service and are lightly loaded, the heater voltage may be reduced as much as 5 per cent below normal to conserve life. As conditions require, the voltage should be increased gradually to maintain output. Toward the end of life, the gradual increase may be carried above rated heater voltage to obtain additional service.

During standby periods of less than 15 minutes, the heater voltage of high-vacuum tubes should be maintained at normal rated value; for longer periods, the heater power should be turned off. In the case of vapor or gas tubes, the heater voltage should be maintained at normal during standby periods up to 12 hours; for longer periods, the heater power should be turned off.

An ionic-heated cathode is one which liberates electrons when it is subjected to intense positive ion bombardment. The bombardment may be so intense as to raise the temperature of the cathode, frequently causing it to become visibly hot. The ionic-heated cathode in radio tubes has found application in gas rectifiers intended primarily for automobile receiver service.

COLD CATHODES

The designation "cold cathode" is commonly used in referring to those cathodes which emit electrons when they are subjected to bombardment by other electrons, ions, or metastable atoms. Cathodes of



TYPES OF CATHODES

(continued from preceding page)

this type are sometimes designated as secondary-emission cathodes. They are used in certain glow-discharge tubes, and also in multiplier phototubes where they contribute to electron multiplication in the successive dynode stages.

Not customarily referred to as cold cathodes, although they are such, is another group of emitters known as photocathodes. By definition, a **photocathode** is one which emits electrons when it is energized with radiant flux, such as light, infra-red radiation, or ultra-violet radiation. Such cathodes are used in phototubes. When used in gas phototubes, these cathodes not only emit under the influence of radiant flux but also as a result of bombardment and thus become partial secondary-emission cathodes.

Photocathodes are classified according to the spectral response characteristics of their respective photoactive surfaces. The S1 photosurface gives high response to red and near infra-red radiation. The S2 photosurface is similar to the S1 surface but extends somewhat further into the infra-red region. The S3 photosurface has a spectral response characteristic which is closest to that of the eye. The S4 photosurface has exceptionally high response to blue and blue-green radiation with negligible response to red radiation.

Exposure of photocathodes to intense light, such as direct sunlight, may decrease the sensitivity of the tubes in which they are used, even though there is no voltage applied. The magnitude and duration of the decrease depend on the length of the exposure. Permanent damage to a phototube may result if it is exposed to radiant energy so intense as to cause excessive heating of the cathode.