

# Frequency response 8 ohm resistive load on both channels

Frequency response @8ohm resistive load on each channel,  
Output from Rigol DG1022 - 1Vrms input RCA in both L+R channel  
no true rms DDM in channel L for current  
no true rms DMM in channel R for Voltage

Frequency	Voltage	Current	Frequency	Voltage	Current	Frequency	Voltage	Current
10	10,57	1,295	11k	10,67	1,222	36k	12,27	1,397
20	10	1,227	12k	10,7	1,22	38k	12,5	1,449
50	10,55	1,285	13k	10,73	1,215	40k	12,72	1,505
100	10,61	1,288	14k	10,76	1,218	42k	12,92	1,562
200	10,61	1,287	15k	10,79	1,22	44k	13,06	1,615
300	10,62	1,289	16k	10,83	1,221	46k	13,11	1,661
400	10,62	1,288	17k	10,85	1,222	48k	13,04	1,692
500	10,62	1,287	18k	10,88	1,221	50k	12,94	1,717
600	10,61	1,287	19k	10,9	1,221			
700	10,62	1,286	20k	10,92	1,223			
800	10,61	1,285	21k	10,95	1,222			
900	10,61	1,284	22k	10,98	1,221			
1k	10,61	1,283	23k	11,03	1,222			
2k	10,59	1,272	24k	11,08	1,22			
3k	10,58	1,263	25k	11,14	1,22			
4k	10,57	1,254	26k	11,21	1,232			
5k	10,57	1,248	27k	11,3	1,242			
6k	10,58	1,241	28k	11,38	1,251			
7k	10,59	1,235	29k	11,48	1,265			
8k	10,6	1,232	30k	11,58	1,28			
9k	10,62	1,228	32k	11,8	1,306			
10k	10,65	1,224	34k	12,03	1,348			