

Ref	Qty	Description	PC board part numbers		PC board part #
				DigiKey P/N	
Note 4	1	47uf 500V Electrolytic cap	338-1973-ND		C1
Note 4	1	120uF 500V Electrolytic cap	493-6794-ND		C2
Note 4	2	1500uF 63V Electrolytic cap	P10334-ND		C12 C22
	2	1500uF 6.3V Electrolytic cap	P10203-ND		C10 C20
Note 1	2	Audience Auricap XO .22µF / 600V	CP-AAXO-22-600V		C11 C21
	1	2 x .047uf 100v ORANGE DROP Capacitors	716P Polypropylene		C3
Note 2	0	150ohm 5W wirewound resistor	1 is not used if you are using the optional power supply choke		R1
Note 3	2	560ohm 5W wirewound resistor	560W-5-ND		R17 R27
	4	100ohm 1/4 W metal film resistor	100XBK-ND		R12 R16 R22 R26
	4	220K or 221K 1/4 W metal film resistor	221KXBK		R11 R15 R21 R25
	2	220ohm 1/4W metal film resistor	221XBK		R10 R20
Run in UL mode	2	10K 3W metal oxide film resistor			R14 R24
	1	150K 3W metal oxide film resistor			R2
	1	10k 1 W metal oxide film resistor	P10KW-1BK-ND		R3
	2	1K 1/4 W metal film resistor	1.00KXBK-ND		R19 R29
	2	330 or 332 ohm 1/4 W metal film resistor	332XBK-ND		R13 R23
	2	100ohm 2 W metal oxide film resistor	100W-2-ND		R18 R28
	1	150K 2W metal oxide film resistor	150KW-2-ND		R4
	0	1200 PIV FRED diode TO-220 pkg			D1 D2
	2	CCS	IXCP10M45S-ND		U10 U20
	2	Heat Sink	HS189-ND		
	3	Octal Socket	P-ST8-193G		V11 V21
	1	Noval Socket	P-ST9-214G		V10
	9	2 pin terminal strip	277-1258-ND		
	3	3 pin terminal strip	277-1259-ND		
	1	Completed PC board			
		Output Transformer X2			
	2	Edcor CXSE25-8-5K.			
		Power Transformer			
	1	Allied 6K7VG			
		Power Choke			
	1	Triad Magnetics C-14X			
		Tubes			
		Power			
	1	EH KT88 Vacuum Tube, Matched Pair	Amazon		
		Pre-Amp			
	1	JJ Electronics T-12AT7 Vacuum Tube ECC81	T-12AT7		
	1	Power Socket with fuse holder	603-1131-ND		
	1	Power Switch			
	1	Power Cord	Q124-ND		
	2	Bussmann 2 Amp Time Delay Fuse 250Vac	BP/MDL-2		
	2	Carbon Fiber Five-Way Binding Posts			
	3	Dayton AudioChassis Mount RCA Jack Pair	RCA-CHRB		
	1	ALPS 50K Potentiometer 6mm Shaft	50KAX2		
		Optional parts used in high end amps			
	1	TEMCo Motor Run Capacitor	RC0096		
	1	GZ-34 or 5AR4 tube			
	1	Rectifier Switch SPST	Carling SPST-P-H531		
	1	Mode Switch DPDT	Carling DPDT-P-H523		
	1	Feedback Switch DPDT	Carling DPDT-P-H523		
		Auxiliary power supply cap			
	1	Inrush current limiter	KC014L-ND		
	2	Diodes	UF4007CT-ND		
	1	CL 90 placed inline with the power xformer	KC019L-ND		