

JJ 12AY7 Phase Splitter/Driver, LM334 Current Sink; JJ 7591S PP, Edcor 10W 10k plate-plate
Ultra Linear 8 Ohm Load on 4 Ohm Tap

1 Watt, 1kHz	2nd Harmonic - 58 dBc	3rd Harmonic - 49 dBc
	2nd Harmonic 0.126 %	3rd Harmonic 0.354 %
	RSS 2nd Harmonic + 3rd Harmonic	0.376 %

2 Watt, 1kHz	2nd Harmonic - 60 dBc	3rd Harmonic - 46 dBc
	2nd Harmonic 0.1 %	3rd Harmonic 0.5 %
	RSS 2nd Harmonic + 3rd Harmonic	0.511 %

3 Watt, 1kHz	2nd Harmonic - 56 dBc	3rd Harmonic - 43 dBc
	2nd Harmonic. 0.158 %	3rd Harmonic. 0.707 %
	RSS 2nd Harmonic + 3rd Harmonic	0.725 %

1 Watt, 2nd Order IMD,	250Hz & 8020Hz,	4:1 (12 dB)	- 52 dBc
1 Watt, 3rd Order IMD,	11kHz & 12kHz,	1:1	- 48 dBc

2 Watt, 2nd Order IMD,	250Hz & 8020Hz,	4:1 (12 dB)	- 50 dBc
2 Watt, 3rd Order IMD,	11kHz & 12kHz,	1:1	- 45 dBc

3 Watt, 2nd Order IMD,	250Hz & 8020Hz,	4:1 (12 dB)	- 47 dBc
3 Watt, 3rd Order IMD,	11kHz & 12kHz,	1:1	- 43 dBc