

Output Impedance:	
Low and High Frequency Output.....	3000 Ω (600 Ω when shunted with 750 Ω resistor).
Internal Generator Frequencies:	
Low Frequency.....	60 cycles.
High Frequency	Approximately 6 kc.
Accuracy:	
AC VTVM and Wattmeter.....	Within 5% of full scale.
I.M. Analyzer.....	Within 10% of full scale.
General:	
Multipliers.....	Precision type.
Meter.....	4 1/2" streamlined case with 200 microampere movement.
Meter Rectifier.....	Germanium diode bridge.
Tube Complement	1 - 12AT7
	1 - 12AU7
	1 - 12AX7
	1 - 6C4
	1 - 6X4
Power Supply.....	Transformer, full wave rectifier.
Power Requirements.....	105-125 volts 50/60 cycles 20 watts.
Dimensions.....	13" wide x 8 1/2" high x 7" deep.
Net Weight	9 lbs.
Shipping Weight.....	13 lbs.

