



This 30W Single Ended toroidal output transformer is newly made for high-end HiFi audio amplifiers. It uses toroidal core with air gaps to improve the audio quality. It will work with the most common output tubes.

SPECIFICATION:

Output power	30 Watt
Turn Ratio	18:1
Ultra Linear tap	40%
Primary impedance	7.5K ohm
Primary DC resistance	167 ohm
Output impedance	4 & 8 ohm
Output DC resistance	0.1 & 0.2 ohm
Max DC current	100mA
Frequency response	10Hz - 20KHz
Suggest Tubes	805, 211

