


Ref Desig.	Part Number	Description
IC1	TL494IDR	Driver IC – 16 pin
Q12, Q13, Q14, Q18, Q19, Q20	K36621 – (2sk3662-f)	Power Supply Transister – <i>Field Effect</i>
Q187, Q188, Q189, Q190	ST W34NB20	Output Transister
Q26	SK C4883A – (2sc4883anf)	Audio Output Driver
Q28	SK A1859A – (2sa1859anf)	Audio Output Driver
D18	FCH20A20	Rectifier Diode
D19	FRH20A20	Rectifier Diode

TL494IDR pin designation and measured Voltage when 12V w/ 10A fuse applied.



Pin 1	0	Pin 9	0.61
Pin 2	0.05	Pin 10	2.1
Pin 3	0.05	Pin 11	3.9
Pin 4	0.1	Pin 12	3.9
Pin 5	0.83	Pin 13	3
Pin 6	1.2	Pin 14	3
Pin 7	0	Pin 15	3
Pin 8	3.37	Pin 16	0