

**Test Point tip Jacks (in red):**  
TP1A – red/blk – 300B filament voltage 1  
TP1B – red/blk – 300B filament voltage 2  
TP2A – blu/yel – 300B pass current 1  
TP2B – blu/yel – 300B pass current 2  
TP3 – blu/yel – driver tube pass current  
TP4 – blu/yel – bias voltage  
TP5 – red/yel – 300B anode voltage  
TP6 – red/yel – B+ voltage  
TP7 – red/yel – driver B+ voltage  
TP8 – red/yel – driver anode voltage  
TP9 – grn chassis (mains) ground  
TP10 – yel circuit ground  
TP11 – driver cathode voltage

**Calibration Procedure (verify this after build):**  
TP6 – set PSU to 0V  
TP4 – set coarse bias fully counter clockwise (max negative bias)  
TP1A – set Coleman to 5V  
TP1B – set Coleman to 5V  
TP6 – set PSU to 380V  
TP2A and TP2B – set coarse bias so these are nearly matched at .07V  
TP2A and TP2B – set fine bias so these are nearly matched at .07V  
TP6 – Verify that B+ is still 380, re-adjust variac to 380V if needed  
Repeat above three steps to get .07V match at 380V B+  
TP3 – verify driver current it should be about .01V  
TP4 – verify bias voltage it should be about -85V (verify after)?  
Verify all other test points for reasonableness

