

P/N	Part	Mouser P/N	Qty	Notes			
R101	100k 2W	603-RSF2WSJR-73-100K		1 Or similar, or reuse original			
R102	150k 2W	603-FMP200JR-52-150K		1 Or similar, or reuse original			
R103-4	4.7M 1/2W	594-HVR3700004704FR5		2 High voltage tolerance, do not reuse original			
R105	910k 2W	279-RR02J910KTB		1 Or similar, or reuse original. lower wattage may be ok			
R1L-R	4.7R 5W	594-AC05AT0004708JAC		2 4.7R power resistor of your choice, SRD-5 can reuse.			
R2L-R	27R 5W	588-TUW5J27RE		2 27R power resistor or similar resistance of your choice, or reuse original, optional but recommended. Makes the transformer a less reactive load.			
C101-6	0.1uf 160v+	505-MKS4F031002CKSSD		6 Any 0.1uf cap that tolerates substantially more than 100v and fits			
C107-8	0.01uf 630v	505-MKS4.01/630/10P		2 13x4mm 10mm spacing, optional			
D101-6	1n4007	637-1N4007		6 Any axial diode rated over 400v, no reason to get fancy. There are reports of leaky diodes sold on ebay and aliexpress so don't go too cheap.			
ZD1	P6KE110	576-P6KE110CA		1 P6KE110 is a standard part, reuse original bidirectional zener for slightly lower bias.			
F1	0034.6009	693-0034.6009		1 Not for SRD-7. 315mA radial fuse 3.2mm lead spacing. Optional wall power safety with unfused stax chassis			
F1S	0031-7601	693-0031.7601		1 Very optional fuse socket. Fingers crossed.			