

Series 7000K - Two 115V primary windings for series or parallel connections.

Power VA	Part Number	Sec-Full Load Voltage	Current mA	Open Circuit Voltage
1.6	70000	2x7	114	2x9.3
	70001	2x9	89	2x12.0
	70002	2x12	67	2x16.0
	70003	2x15	53	2x20.0
	70004	2x18	44	2x23.9
70005	2x22	36	2x29.3	
3.2	70010	2x7	229	2x10.1
	70011	2x9	178	2x13.0
	70012	2x12	133	2x17.3
	70013	2x15	107	2x21.6
	70014	2x18	89	2x25.9
70015	2x22	73	2x31.7	
5.0	70020	2x7	357	2x10.3
	70021	2x9	278	2x13.2
	70022	2x12	208	2x17.6
	70023	2x15	167	2x22.1
	70024	2x18	139	2x26.5
70025	2x22	114	2x32.3	
7.0	70030	2x7	500	2x9.5
	70031	2x9	389	2x12.5
	70032	2x12	292	2x16.2
	70033	2x15	233	2x20.3
	70034	2x18	194	2x24.3
70035	2x22	159	2x29.7	
10.0	70040	2x7	714	2x8.5
	70041	2x9	556	2x11.0
	70042	2x12	417	2x14.6
	70043	2x15	333	2x18.3
	70044	2x18	278	2x22.0
70055	2x22	227	2x26.8	
15.0	70050	2x7	1071	2x8.7
	70051	2x9	833	2x11.2
	70052	2x12	625	2x14.9
	70053	2x15	500	2x18.6
	70054	2x18	417	2x22.3
70055	2x22	341	2x27.3	
25.0	70060	2x7	1785	2x8.3
	70061	2x9	1377	2x10.7
	70062	2x12	1041	2x14.3
	70063	2x15	832	2x17.8
	70064	2x18	694	2x21.4
70065	2x22	568	2x26.2	
35.0	70070	2x7	2500	2x8.2
	70071	2x9	1944	2x10.6
	70072	2x12	1458	2x14.1
	70073	2x15	1167	2x17.7
	70074	2x18	972	2x21.2
70075	2x22	795	2x25.9	
50.0	70080	2x7	3571	2x8.1
	70081	2x9	2777	2x10.4
	70082	2x12	2083	2x13.9
	70083	2x15	1666	2x17.3
	70084	2x18	1388	2x20.8
70085	2x22	1136	2x25.4	