

CD_63_67_xformer

Custom toroidal	Sec. voltage (V)	No. of wdg.	Current (mA)	Power (VA)
+/-12V	17,5	2	200	7,00
+/-10V or +5V	9,5	2	650	12,35
Vf display	3,5	1	200	0,7
Vftd display	14,0	1	50	0,7
Ext. clock+DAC 5mA	9,5	1	200	1,9
DAC D 35mA	9,5	1	200	1,9
DAC A 2mA	9,5	1	200	1,9
Total VA:				26,45

CD63_67_voltages

CD63	STOP	PLAY		Power (VA)	Remarks
+/-12V	19,0V/35mA	18,9V/35mA		1,33	No HDAM, standard 78/7912 regs.
+/-10v	9,6V/70mA	9,4V/115mA	Max. 240mA	4,51	
Vf	3,4V/165mA	3,4V/165mA		0,56	
Vftd	13,9V/26mA	13,7V/25mA		0,36	
Total VA:				6,76	

CD67	STOP	PLAY		Power (VA)	
+/-12V	16,9V/35mA	16,9V/35mA		1,18	No HDAM, LM317/337 regs.
+5V	9,1V/95mA	9,1V/160mA	Max. 225mA	4,1	
Vf	3,5V/165mA	3,5V/165mA		0,58	
Vftd	13,7V/26mA	13,6V/25mA		0,36	
Total VA:				6,22	

Custom toroidal	Sec. voltage (V)	No. of wdg.	Current (mA)	Power (VA)
+/-12V	17,5	2	200	7,00
+/-10V or +5V	9,5	2	650	12,35
Vf display	3,5	1	200	0,7
Vftd display	14,0	1	50	0,7
Ext. clock+DAC 5mA	9,5	1	200	1,9
DAC D 35mA	9,5	1	200	1,9
DAC A 2mA	9,5	1	200	1,9
Total VA:				26,45