

PART LIST
MODEL G60-212 (PRE-AMP)

SCHEMATIC REFERENCE	DESCRIPTION	ACOUSTIC PART NO.	SCHEMATIC REFERENCE	DESCRIPTION	ACOUSTIC PART NO.
D 1 & 2	LED, red large	480066	C 24	Capacitor Elect 2.2UF 50V	159002
D 3 & 4	Rectifier Diode Zener 10V	480086	C 26	" Disc 27 Pf 500V	157003
D 5 & 6	" " 15V	480085	D 7	Rectifier Diode Zener 4.3V	480036
IC 1,2,3 & 4	IC, OP Amp LF 351N	480063	C 28	Capacitor Elect 47UF 50V	159006
IC 5	IC, Power Amp LM 380N	480064	C 29 & 30	" Elect 100UF 50V	159007
Q 1,2,4 & 6	Transistor, FET N, 2N 5457	480024	R 1	Resistor $\frac{1}{2}$ W 470 K 5%	476447
Q 3,5 & 8	Transistor, NPN 2N2484	480023	R 2	" $\frac{1}{2}$ W 1.5 K 5%	476215
Q 7	Transistor FET P	480033	R 3,22,24, 27,45	" $\frac{1}{2}$ W 10 K 5%	476310
Q 9 & 10	Transistor, PNP 2N4248	480032	R 4,17,16, 30,31,34, 53 & 51	Pot Rotary, 100K	475062
C 1,8,14 & 17	Capacitor, Poly .22UF 100V	152027	R 5 & 43	Resistor, $\frac{1}{2}$ W 100K 5%	476410
C 2	" , Elect, 4.7UF 50V	159003	R 6,11 & 44	" $\frac{1}{2}$ W 220K 5%	476422
C 3 & 27	" , Disc .01UF 500V	157016	R 7,10,14, 33,35,38, 40,49,54	" $\frac{1}{2}$ W 47K 5%	476347
C 4,6,15,19, 23 & 25	" , Elect 1UF 50V	159001			
C 5	" , Disc .0068UF 500V	157015	R 8,54 & 52	" $\frac{1}{2}$ W 68K 5%	476368
C 7 & 18	" , Disc 560PF 500V	157017	R 9 & 13	" $\frac{1}{2}$ W 8.2K 5%	476282
C 9 & 16	" Poly .1UF 100V	158005	R 12 & 50	" $\frac{1}{2}$ W 15 K 5%	476315
C 10	" Disc 390PF 500V	157009	R 18,19,20,21	" $\frac{1}{2}$ W 82 K 5%	476382
C 11	" Disc 100PF 500V	157006			

PART LIST
MODEL G60-212

(PRE - AMP) (cont'd)

SCHEMATIC REFERENCE	DESCRIPTION	ACOUSTIC PART NO.	SCHEMATIC REFERENCE	DESCRIPTION	ACOUSTIC PART NO.
C 12	Cap. Disc 680PF 500 V	157010	C 13	Cap. Disc. .001UF 500V	157001
C 21	Cap. Disc .0015UF 500V	157012	C 22	Cap. Disc .0027UF 500V	157013
R 15 & 23	Pot Rotary 10K	475067	R 25 & 39	Resistor 1/2W 150K 5%	476415
R 26	Resistor 1/2W 39K 5%	476339	R 28	Resistor 1/2W 100 ohm 5%	476110
R 29	Resistor 1/2W 1K 5%	476210	R 32	Pot Rotary 4K	475063
R 36 & 37	Resistor, 1/2W 330 ohm 5%	476133	R 41 & 42	Resistor 1/2W 820 ohm 5%	476182
R 46	Resistor, 1/2W 18K 5%	476318	R 47	Resistor 1/2W 220 ohm 5%	476122
R 48	Resistor, 1/2W 10 meg 5%	476610			