



Workbench Notes:

Manufacturer: Markaudio

$f(s) = 46.3$ Hz

$Q(ts) = 0.366$

$V(as) = 16.27$ liters (0.5744 cubic feet)

SPL = 87.52 dB SPL 1W/1m

Nominal Diam. = 118 mm (0 in.)

Model: Sota 11R

$R(e) = 7.269$ Ohms

$Q(es) = 0.4423$

Piston Diam. = 118 mm (4.646 in.)

SPL = 87.93 dB SPL 2.83 Vrms

$C(ms) = 0.968$ mm/N

$Z(max) = 42.14$ Ohms

$L(e) = 0.214$ mH at 10kHz

$Q(ms) = 2.122$

BL = 7.64

$n(0) = 0.348$ %

$M(ms) = 12.21$ grams

My Company

My Address

My City State Zip

My Phone

Measurements by: My Name

Title: My Title