



Workbench Notes:

Manufacturer: Markaudio

$f(s) = 47.04$  Hz

$Q(ts) = 0.3772$

$V(as) = 15.76$  liters (0.5565 cubic feet)

SPL = 87.45 dB SPL 1W/1m

Nominal Diam. = 118 mm (0 in.)

Model: Sota 11R

$R(e) = 7.285$  Ohms

$Q(es) = 0.4565$

Piston Diam. = 118 mm (4.646 in.)

SPL = 87.85 dB SPL 2.83 Vrms

$C(ms) = 0.938$  mm/N

$Z(max) = 41.95$  Ohms

$L(e) = 0.2103$  mH at 10kHz

$Q(ms) = 2.172$

BL = 7.588

$n(0) = 0.3426$  %

$M(ms) = 12.21$  grams

My Company

My Address

My City State Zip

My Phone

Measurements by: My Name

Title: My Title