

Eu #	BASE	Heater Current	Triode Mu	Gm	Pd	Pentode Gm	Pd	
6AX8	ECF80	450	40	8500	2.7	4800	2.8	
6BL8		450	40	5000	1.5	6200	1.7	
6EA8		450	40	8500	3	6400	3.1	
6GH8		450	46	8500	2.5	7500	2.5	
6GJ8		600	40	8500	2.5	7500	2.5	
6HL8	9AE	600	40	7000	2.5	10000	2.5	
6JW8	ECF802	9DC	430	70	3500	1.4	5500	1.2
6KD8	9DC	400	40	7500	2.5	5000	3	
6KE8		400	40	8000	2	12000	2	
6LM8		9AE	450	46	8500	2.5	6000	2.5
6LN8	LCF80	450	20	5000	1.5	6200	1.7	
6LX8	LCF802	9DC	450	70	3500	1.4	5500	1.2
6MG8	9DC	450	40	8500	2.5	6200	2	
6MQ8	9AE	535	40	8500	2.7	10000	2.5	
6MU8	9AE	600	35	6000	2.5	9000	3.75	
6U8	ECF82	450	40	5000	2.5	7500	3	
6678		450	40	8500	3	5200	3	
7687		500	18	2500	2.4	5800	3	

6AU8	600	43	5300	2.5	8000	3
6AW8	600	70	4000	1	9000	3.25
6BA8	600	18	2700	2	9000	3.25
6BH8	600	17	3300	2.5	7000	3
6CX8	750	40	4600	2	10000	5
6EB8	750	100	2700	1	12500	5
6GN8	750	100	2700	1	11500	5
6HF8	750	70	4000	1	12500	5
6HZ8	1125	70	400	1	12600	8
6JA8	750	70	3700	1	14000	5
6JE8	780	70	4200	1	12000	5
6JL8	750	35	4700	2	11500	5
6JT8	725	100	2700	1	20000	4
6JV8	600	70	4000	1	10700	4
6KR8	750	46	10400	2	20000	5
6KT8	600	100	3200	1	10000	2.5
6KS8	600	70	4000	1.1	9500	3.75
6KV8	775	70	4000	1	23000	5
6LB8	725	30	5000	2	20000	4
6LF8	600	70	4000	1.1	11000	3.75
6LQ8	700	46	10400	2	21000	5
6LY8	750	100	1700	1	20000	5
6MV8	600	100	4000	1	9000	2.5